

LBB 1956/00 Plena Voice Alarm Call Station

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Stylish six-zone call station for the Plena Voice Alarm System
- ▶ Six zone selection keys, all-call key and momentary PTT-key for calls
- ▶ Selectable gain, speech filter, limiter, and output level for improved intelligibility
- ▶ LED indications for zone selection, fault, and emergency state
- ▶ Call station extension provides seven additional zone and zone group keys

The LBB 1956/00 call station is a stylish, high-quality call station with a stable metal base design, a flexible microphone stem and a unidirectional condenser microphone. It can make calls to selected zones (one to six and all-call) in a public address system built with the Plena Voice Alarm System. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops. The LBB 1957/00 Plena Voice Alarm System Keypad is an extension adding seven additional keys.

Functions

Each call station supports six zone selections. The number of selectable zones or zone groups can be increased by connecting call station keypads (LBB 1957/00). Up to eight keypads can be added with each keypad adding seven zone or zone-group keys.

This call station features selectable gain, a selectable speech filter, and a limiter for improved intelligibility. The call station has a balanced line level output, making it possible to position it up to 1000 meters

from the controller, using CAT-5 extension cables. With shielded cable, the call station can also be used in an EMC level 5 (heavy industry) environment.

DIP switches at the base of the call station select different microphone gain levels, the call station ID, and the speech filter. A service accessible rotary control provides microphone level attenuation. LEDs on the call station show which zones have been selected. Three additional LEDs give visible feedback on the active state of the microphone and the system. Green flashing means standby (chime is sounding). Green indicates microphone active. Amber indicates that the system has detected a fault, and red indicates that the system is in the emergency state.

Controls and indicators

- Four status LEDs
- PTT-key
- PTT status LED
- Six zone selection keys
- Six zone selection LEDs
- All-call key
- Eight DIP switches

- Rotary volume control

Interconnections

- Two RJ45 jacks
- 24 VDC input
- Keypad connector

Certifications and approvals

| | |
|----------|--------------------|
| Safety | acc. to EN 60065 |
| Immunity | acc. to EN 55103-2 |
| Emission | acc. to EN 55103-1 |

| Region | Certification | |
|--------|---------------|---------------------------|
| Europe | CE | Declaration of Conformity |

Parts included

| Quantity | Components |
|----------|--|
| 1 | LBB 1956/00 Call Station |
| 1 | Cable terminated with a lockable CAT-5 connector |

Technical specifications

Electrical

| Power Supply | |
|----------------------------|---|
| Voltage range | 24 VDC supplied by LBB 1990/00 (or 18 to 24 VDC or VAC external power supply) |
| Current consumption | <30 mA (plus <15 mA per keypad) |
| Performance | |
| Nominal sensitivity | 85 dB SPL (gain preset 0 dB) |
| Nominal output level | 700 mV |
| Input sound level (max) | 110 dB SPL |
| Gain preset | +6 / 0 / -15 dB |
| Limiter threshold | 2 V |
| Compression ratio limiter | 1:20 |
| Distortion | <0.6% (maximum input) |
| Input noise level (equiv.) | 25 dB SPLA |
| Frequency response | 100 Hz to 16 kHz |
| Speech filter | -3dB at 315 Hz, high-pass, 6 dB/oct |
| Output impedance | 200 ohm |
| Selections | |
| Chimes | Any wave file |
| Priorities | 7 |

Mechanical

| | |
|----------------------|--|
| Base dimensions | 40 x 100 x 235 mm (1.57 x 3.97 x 9.25 in) |
| Weight | Approx. 1 kg |
| Mounting | Standalone |
| Color | Charcoal with silver |
| Stem length with mic | 390 mm (15.35 in) |
| Cable length | 5 m (16.4 ft) |

Environmental

| | |
|-----------------------|--------------------------------------|
| Operating temperature | -10 °C to +45 °C (14 °F to +113 °F) |
| Storage temperature | -40 °C to +70 °C (-40 °F to +158 °F) |
| Relative humidity | <95% |

Ordering information

LBB 1956/00 Plena Voice Alarm Call Station

Flexible microphone stem and unidirectional condenser microphone, metal base design, can make calls to selected zones (one to six and all-call).
Order number **LBB1956/00**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com